

DAM005N120F1

N-Channel Enhancement Mode MOSFET


Features

- · Fast Switching
- 100% Avalanche Tested
- · Improved dv/dt Capability


Applications

- Switch Mode Power Supply(SMPS)
- Uninterruptible Power Supply (UPS)
- Power Factor Correction(PFC)


Preliminary



V_{DSS}	1200V
I _{D(@25°C)}	5A
$R_{DS(ON)}$ max.	3.2Ω



Package Dimensions



	Dimensions						
Ref.	Millimeters			Inches			
	Min.	Тур.	Max.	Min.	Тур.	Max.	
Α	4.50		4.90	0.177		0.193	
В	0.74	0.80	0.83	0.029	0.031	0.033	
С	0.47		0.65	0.019		0.026	
C2	2.45		2.75	0.096		0.108	
C3	2.60		3.00	0.102		0.118	
D	8.80		9.30	0.346		0.366	
Е	9.80		10.4	0.386		0.410	
F	6.40		6.80	0.252		0.268	
G		2.54			0.1		
Н	28.0		29.8	1.102		1.173	
L1		3.63			0.143		
L2	1.14		1.70	0.045		0.067	
L3		3.30			0.130		
V1		45°			45°		

Absolute Maximum Ratings

(Tc = 25°C unless otherwise specified)

Parameter	Symbol	Ratings	Unit
Drain Source Voltage	V _{DS}	1200	V
Gate Source Voltage	V _{GS}	± 30	v
Drain Current Continuous @ Tc = 25°C	lь	5	Α
Drain Current Pulsed Note2	Ірм	20	Α
Single Pulse Avalanche Energy	Eas	150	mJ
Power Dissipation @ Tc= 25°C	Po	350	w
Storage Temperature Range	Тѕтс	-55 to +150	°C
Operating Junction Temperature Range	TJ	-55to +150	°C
Thermal Resistance Junction to Case	R hetaЈс	0.6	°C/W

Note: 1. Repetitive rating pulse width limited by maximum junction temperature

2. Repetitive rating : pulse width limited by junction temperature

DAM005N120F1

Electrical Characteristics @ Tc =25°C (unless otherwise specified)

Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit		
OFF Characteristics								
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} =0V · I _D =0.25mA	1200	-	-	V		
Drain-Source Leakage Current	I _{DSS}	V _{GS} =0V , V _{DS} =1200V	-	-	5	μΑ		
Gate To Source Leakage Current	I _{GSS}	V _{GS} =±30V , V _{DS} =0V	-	-	±100	nA		
ON Characteristics (Pulse Width < 380µs, Duty Cycle < 2%.)								
Gate Threshold Voltage	V _{GS(th)}	V _{DS} =V _{GS} , I _D =0.25mA	3.0	4.0	5.0	V		
Drain-Source On-State Resistance	R _{DS(on)}	V _{GS} =10V , I _D =1.5A	-	2.6	3.2	Ω		
Dynamic Characteristics								
Input Capacitance	C _{iss}	V _{DS} =25V	-	1206	-	pF		
Output Capacitance	C _{oss}	V _{GS} =0V	-	103	-			
Reverse Transfer Capacitance	C _{rss}	Freq.=1MHz	-	22.3	-			
Switching Characteristics								
Turn-On Delay Time	t _{d(on)}	V_{DD} =600 V I_{D} =3 A R_{G} =10 Ω	-	23.6	-	ns		
Rise Time	t _r		-	8.6	-			
Turn-Off Delay Time	t _{d(off)}		-	50.8	-			
Fall Time	t _f		-	18	-			
Total Gate Charge	Qg	V _{DS} =960V	-	39	-			
Gate to Source Charge	Q _{gs}	V _{GS} =10V	-	7.5	-	nC		
Gate to Drain Charge	Q_{gd}	I _{DS} =3A	-	23.4	-			
Source-Drain Diode Characteristics								
Diode Forward Voltage	V _{SD}	V _{GS} =0V • I _S =3A	-	-	1.6	V		
Continuous Source Current (Body Diode)	I _{SD}		-	-	5	Α		
Max. Pulsed Current (Body Diode)	I _{SM}		-	-	20	Α		
Reverse Recovery Time	T _{rr}	Is=3A	-	526	-	ns		
Reverse Recovery Charge	Qrr	dir/dt=100A/μs	-	2	-	μC		

Note : 3. Isp = 6A, di/dt \leq 200A/us, Vpp \leq BVps, Start TJ =25 $^{\circ}$ C



Typical Performance Characteristics

Figure 1. Output Characteristics




Figure 3. Drain-to-Source On Resistance vs Drain Current




Figure 5. Gate Charge Characteristics




Figure 2. Transfer Characteristics




Figure 4. Body Diode Forward Voltage vs Source Current and Temperature





Figure 6. Capacitance Characteristic



www.dacosemi.com.tw



Typical Performance Characteristics

Figure 7. Normalized Breakdown Voltage vs Junction Temperature




Figure 9. Maximum Continuous Drain Current vs Case Temperature Temperature




Figure 8. Normalized On Resistance vs Junction Temperature




Figure 10. Maximum Safe Operating Area





Figure 11. Maximum Effective Transient Thermal Impedance, Junction-to-Case



Rev1.0 Jan 2024 - 4 -





Disclaimer

DACO Semiconductor reserves the right to make modifications, enhancements, improvements, corrections, or other changes to this document and any product described herein without prior notice.

DACO Semiconductor makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any liability, including without limitation special, consequential or incidental damages.

Purchasers are responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations, and safety requirements or standards, regardless of any support or application information provided by DACO Semiconductor. "Typical" parameters that may be provided in DACO Semiconductor datasheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typical" must be validated for each customer application by the customer's technical experts.

DACO Semiconductor products are not designed, authorized, or warranted to be suitable for use in life support, life-critical or safety-critical systems, or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accepts no liability for the inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers who buy or use DACO Semiconductor products for any unintended or unauthorized applications are required to indemnify and absolve DACO Semiconductor, its suppliers, and distributors from any claims, costs, damages, expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or by any information storage and retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.