

### MBRT40040(R)L

## LOW VF SCHOTTKY DIODE MODULE TYPE 400A / 40V

### **Features**

High Surge Capability
Type 40V VRRM
Isolation Type Package
Electrically Isolation Base Plate


### **Maximum Ratings**

Junction Operating Temperature : -40°C to +100°C Storage Temperature : -40°C to +150°C

Part Number	Maximum Recurrent Peak Reverse Voltage	Maximum RMS Voltage	Maximum DC Blocking Voltage
MBRT40040(R)L	40V	28V	40V

# THREE TOWER

Dimensions in mm (1 mm = 0.0394")



### Electrical Characteristics @ 25 $^{\circ}$ C Unless Otherwise Specified

Average Forward Current (Per pkg) (Per diode)	<b>I</b> F(AV)	400A 200A	Tc = 100°C
Peak Forward Surge Current (Per diode)	İFSM	3000A	8.3ms , half sine
Maximum (Per diode) Instantaneous Forward Voltage*	VF	0.60V	IFM=200A;ТJ = 25°С
Maximum Instantaneous Reverse Current At Rated DC Blockig Voltage* (Per diode)	lr	3mA 300mA	T <sub>J</sub> = 25°C T <sub>J</sub> = 100°C
Maximum Thermal Resistance Junction To Case (Per diode)	Rejc	0.35°C/W	
Isolation Voltage	Viso	2500V	A.C. 1 minute
Weight		103g	

Teminal Teminal Teminal Anode 1 Catode 2 Anode 3 Common Cathode R=Common Anode

<sup>\*</sup>Pulse Test: Pulse Width 300 µsec, Duty Cycle < 2%

## MBRT40040(R)L

Figure .2-Forward Derating Curve

240
200
160
80
Single Phase, Half Wave
60Hz Resistive or Inductive Load
0 25 50 75 100 125 150
°C
Case Temperature - °C

Figure.3- Peak Forward Surge Current

Volts

Instantaneous Forward Voltage -Volts





Figure.4- Typical Reverse Characteristics







#### **Disclaimer**

DACO Semiconductor reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein.

DACO Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does DACO Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages.

Purchasers is responsible for its products and applications using DACO Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by DACO Semiconductor. "Typical" parameters which may be provided in DACO Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts.

DACO Semiconductor products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of DACO Semiconductor's product can reasonably be expected to result in personal injury, death or severe property or environmental damage. DACO Semiconductor accept no liability for inclusion and/or use of DACO Semiconductor's products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Purchasers buy or use DACO Semiconductor products for any such unintended or unauthorized application, Purchasers shall indemnify and hold DACO Semiconductor and its suppliers and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that DACO Semiconductor was negligent regarding the design or manufacture of the part.

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of DACO Semiconductor Co., Ltd.

www.dacosemi.com.tw